

RB87

RETCVIS

GMRS Handheld Two Way Radio

Description:

- The operation is simple and the sound quality is good.
- CTCSS/DCS signaling to effectively avoid redundant calls from other stations.
- VOX enables normal calls without the need for PTT keys.
- Eliminate the tail tone to avoid the impact noise from the loudspeaker at the end of the call.

Feature:

- Frequency Range: GMRS
- Monitor
- VOX
- Scan function
- Time-out-Time(TOT) function
- CTCSS/DCS function
- Channel Lockout



RB87

GMRS Handheld Two Way Radio

Specification:

Frequency Range:	GMRS
Supply Pow:	DC7.4V
Memory Channel:	30
Work Mode:	Co/Differ-frequency Simplex Communication
Battery:	Li-ion 1200mAh
Ground Method:	Cathode

Transmitter

Power:	5W/0.5W
Modulation Mode:	FM(F3E)
Max.Frequency Deviation(Wide/Narrow):	$\leq 5\text{KHz}/\leq 2.5\text{KHz}$
Spurious Radiation:	$\leq 7.5\text{uW}$
Preemphasis Character:	Per Octave 6dB
Emission Current:	$\leq 1.5\text{A}$

Receiver

Sensitivity:	$< 0.16\text{uV}(12\text{dB SINAD})$
Audio Power:	1W
Audio Distortion:	$< 10\%$
Inter-Modulation:	$\geq 60\text{dB}$

Standard Accessories:

- 1 x RB87 two way radio
- 1 x Battery
- 1 x Belt Clip
- 1 x User's Manual
- 1 x Mini USB Charging Cable



CE FC RoHS



Shenzhen Retevis Technology Co.,Ltd.

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA